



## PRODUCT DATASHEET

### SMART+ WIFI Multipower Socket EU White

SMART+ WIFI Multipower Socket GEN2 | Multi Power Socket with smart 4 EU sockets and USB ports with WiFi technology



#### Areas of application

- Wherever non-smart devices need to be integrated into compatible smart home systems
- USB ports available for power supply

#### Product benefits

- Smart Multi power socket: Simple connection of electric devices via smart sockets and smart USB ports
- Monitors energy usage of connected devices and tracks the energy consumption
- Integrates conventional electric equipment into compatible smart home systems
- Enables switching of conventional light sources and other electric devices
- Wireless control via app or voice control

#### Product features


- Smart 4 standard sockets and smart 4 USB ports for charging (2 ports each Type A and C)
- USB charger: Fast charging with USB Power Delivery (USB PD) up to 20W power
- Power sockets can be controlled individually and USB ports are controlled as one group
- High switching power: up to 3,680 W / 16 A
- Energy meter
- Scheduling
- 1.5 m power cable for flexible installation
- Network protocol: WiFi (2.4 GHz)
- Controllable via SMART+ App (with minimum Android 8.0 or iOS 14.0)
- Controllable via voice control available: Google Assistant or Amazon Alexa
- Controllable via SMART+ WiFi Remote Controller

TECHNICAL DATA

Electrical data

|                 |       |
|-----------------|-------|
| Nominal voltage | 230 V |
| Nominal current | 16 A  |
| Mains frequency | 50 Hz |

Dimensions & Weight



|                |          |
|----------------|----------|
| Product weight | 586.00 g |
| Length         | 315 mm   |
| Width          | 62 mm    |
| Height         | 40 mm    |

Lifespan

|                            |       |
|----------------------------|-------|
| Number of switching cycles | 10000 |
|----------------------------|-------|

Colors & materials

|               |       |
|---------------|-------|
| Product color | White |
|---------------|-------|

Temperatures & operating conditions

|                           |             |
|---------------------------|-------------|
| Ambient temperature range | -5...+40 °C |
|---------------------------|-------------|

Capabilities

|                                  |                            |
|----------------------------------|----------------------------|
| Type of connection               | Plug                       |
| Compatible smart home technology | Amazon Alexa / Google Home |

Certificates & Standards

|                    |      |
|--------------------|------|
| Standards          | CE   |
| Protection class   | I    |
| Type of protection | IP20 |

Safety advice

- Disconnect devices which generate heat from the mains, i.e. from the SMART+ Multi Power Socket, after use in order to avoid them being accidentally switched on.

- Very high capacitive and inductive loads may in some cases lead to destruction of the device or reduction in the number of switching cycles.
- Do not use the SMART+ Multi Power Socket in conjunction with medical equipment.
- To be connected to an automatic circuit breaker (for max. 16 A)
- Product in protection class I. All electrically conductive, metallic housing parts that can absorb voltage during operation or during maintenance in the event of a fault must be continuously connected to the protective earthing conductor.

## DOWNLOAD DATA

| Documents and certificates                                                        |                                        | Document name                               |
|-----------------------------------------------------------------------------------|----------------------------------------|---------------------------------------------|
|   | User instruction / safety instructions | SMART+ MULTIPOWER SOCKET                    |
|   | Addon technical information            | Wifi remote control compatibility list      |
|   | Addon technical information            | Wifi remote control compatibility list (DE) |
|   | Legal information                      | Safety insert G11234413                     |
|   | Declarations of conformity             | SMART WIFI MULTIPOWER SOCKET EU             |
|  | EU Data Act                            | SMART WiFi Plugs                            |

## LOGISTICAL DATA

| Product code  | Packaging unit (Pieces/Unit) | Dimensions (length x width x height) | Gross weight | Volume                |
|---------------|------------------------------|--------------------------------------|--------------|-----------------------|
| 4099854418198 | Folding box<br>1             | 76 mm x 76 mm x 377 mm               | 633.00 g     | 2.18 dm <sup>3</sup>  |
| 4099854418204 | Shipping box<br>4            | 390 mm x 165 mm x 165 mm             | 2764.00 g    | 10.62 dm <sup>3</sup> |

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

## References / Links

- Further information and frequently asked questions (FAQs) at [www.ledvance.com/en-int/home-lighting/services/faq](http://www.ledvance.com/en-int/home-lighting/services/faq)

## DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.